



# TX - 100

## TRIP AMPLIFIER

### Features

- Single Input, Dual Output
- Signal Conversion with Isolation
- Universal Input
- Reliable & Cost Effective System
- 24 V DC Operated
- Compact Size & Easy Maintenance
- Din Rail Mount
- Potential free relay outputs 2 Nos.



### Description

**E**lectronet series TX-100 are Trip Amplifiers with single input, dual trip output specially used for various industrial applications. It can interface inputs like Current or Voltage & provide isolated output in terms of Current or Voltage. The compact design saves inner space required in panel to mount the instrument.

### Technical Specifications

No. of Input	01 No.
No. of Output	02 Nos.
Type of Input	Universal
	1) RTD (PT-100 / PT-200 / CU-53) 2 or 3 Wire
	2) Thermocouple (J / K / R / S / T / E / B Type Thermocouple)
	3) Current (0-20 mA / 4-20 mA)
	4) Voltage (0-5 V DC / 0-10 V DC/1-5V DC)
Type of Output	4-20 mA / 0-5 V, Isolated
Trip Output	Potential free Relay Contacts (1 c/o, 1 Amp.)
Display	4 X 1 Digit, 0.3", 7 Segment Red LED
Isolation	1.5 KV between Input, Output & Power Supply
Power Supply	24 V DC, External
Accuracy	Better than $\pm 0.25\%$ of F. S.
Power Consumption	< 15 VA
Response Time	< 100 mSec
Temperature Coefficient	$\pm 0.01\%$ per $^{\circ}\text{C}$
Enclosure	ABS, Plastic
Dimensions	75mm(H) X 55mm(W) X 110mm(D)
Mounting	Din Rail Type
Weight	500 gms
Operating Conditions	Temperature -20 to 55 $^{\circ}\text{C}$ / Humidity 5 to 95% non condensing
Temperature Drift	0.01% of F. S. / $^{\circ}\text{C}$
Range	programmable for mA and voltage(-999 to 9999) & Fixed for RTD & thermocouple input.
<b>OPTIONAL</b>	
Retransmission Output	4-20 mA / 0-5 V, Isolated
Communication Port	RS 485 supporting MODBUS RTU Protocol

## Ordering Information

Sample Order Code :  

Parameter	Code	Description	Parameter	Code	Description		
G	Output 1 (Either or)	G1	4 to 20mA	H	Output 2 (Either or)	H1	4 to 20mA
		G2	0 to 5V			H2	0 to 5V
		GX	NA			HX	NA

**Note :**

- Due to our continuous product revisions, design specification and model numbers are subject to change without notice.
- Accuracy defined at Lab Conditions.
- For other requirement please consult factory.

## Applications

Food Industry	Chemical Industry	Atomic Energy	Manufacturing Industry
Automation Industry	Thermal Power Energy	Process Industry	Water Treatment Industry

## ELECTRONET EQUIPMENTS PVT. LTD.

## Factory Address:

Plot No. 8, (SEZ) Phase 1, Kesurdi MIDC,  
Khandala, Dist.- Satara  
Pin: 412 801, Maharashtra, India.

## Registered Office:

Plot No. 84, 85, 86, Tiny Industrial Estate,  
Kondhwa Budruk,  
Pune-411 048, Maharashtra, India.



+91-20-26931476/2039



ho@eeplindia.com



+91-20-26934122



www.eeplindia.com